




MIT Kavli Institute



Chandra X-Ray Center

MEMORANDUM

July 15, 2014

To: Jonathan McDowell, SDS Group Leader
From: Glenn E. Allen, SDS
Subject: `acis_build_chip_gti`
Revision: 2.1
URL: <http://space.mit.edu/CXC/docs/docs.html#gti>
File: `/inconceivable/d0/SDS/specs/acis_build_chip_gti/acis_build_chip_gti.2.1.tex`

1 `acis_build_chip_gti`

1.1 Description

For an ACIS CCD, a good-time interval (GTI) is a continuous set of frames during which the detector operated nominally. The GTIs can differ from one CCD to another if more than one is used for an observation.

1.2 Input

1. A Level 1 exposure-statistics file (`acis*stat1.fits`)
2. A Level 1 event-data file (`acis*evt1.fits`)
(This file is also the output file.)
3. A parameter-block file (`acisf*pbk0.fits`)
4. One or more Level 1 aspect-solution file(s) (`pcad*asol1.fits`)
5. A parameter file that includes a list of the CALDB files used by `pixlib`
6. The `CCD_ID` of the aim-point CCD

1.3 Output

The input Level 1 event-data file is modified to include

- several exposure-related keywords and
- one GTI HDU for each valid CCD.

1.4 Parameters

1. `infile`,f,a,“”,,,“Name of input exposure-statistics file”
2. `outfile`,f,a,“”,,,“Name of event-data file to be modified”
3. `pbkfile`,f,a,“”,,,“Name of input parameter-block file”
4. `asppfile`,f,a,“”,,,“Name(s) of input aspect-solution file(s)”
5. `geompar`,f,h,“geom”,,,“Name of input pixlib parameter file”
6. `nominalchip`,s,h,“default”,default|0|1|2|3|4|5|6|7|8|9,“Aim-point CCD_ID”
7. `verbose`,i,h,0,,,
8. `mode`,s,h,“ql”,,,

1.5 Processing

1. Error checking:

(a) `infile`:

- i. If the `infile` does not exist, then `acis_build_chip_gti` exits with an error message.
- ii. If the `infile` exists, but the file permissions do not allow it to be read, then `acis_build_chip_gti` exits with an error message.
- iii. If the `infile` does not have an HDU h_{in} with the keyword

$$\text{CONTENT} = \text{EXPSTATS}, \tag{1}$$

then `acis_build_chip_gti` exits with an error message.

- iv. If HDU h_{in} does not include the header keywords

- `FLSHTIME`,
- `TIMEDEL`, and
- `TIMEPIXR`,

then `acis_build_chip_gti` exits with an error message. Hereafter the values of these keywords are referred to as `FLSHTIMEin`, `TIMEDELin`, and `TIMEPIXRin`, respectively.

- v. If HDU h_{in} does not include a binary table with the columns

- `CCD_ID`,
- `EVTSENT`,
- `EXPNO`, and
- `TIME`,

then `acis_build_chip_gti` exits with an error message. Hereafter these columns are referred to as `CCD_IDin`, `EVTSENTin`, `EXPNOin`, and `TIMEin`, respectively.

(b) `outfile`:

- i. If the `outfile` does not exist, then `acis_build_chip_gti` exits with an error message.
- ii. If the `outfile` exists, but the file permissions do not allow it to be read and modified, then `acis_build_chip_gti` exits with an error message.
- iii. If the `outfile` does not have an HDU h_{out} with the keyword

$$\text{CONTENT} = \text{EVT1}, \tag{2}$$

then `acis_build_chip_gti` exits with an error message.

- iv. If HDU h_{out} of the `outfile` does not include the header keyword
- `DATAMODE`,
- then `acis_build_chip_gti` exits with an error message. Hereafter the value of this keyword is referred to as `DATAMODEout`.

v. If

$$\text{DATAMODE}_{\text{out}} \neq \text{CC33_FAINT} \text{ and} \tag{3}$$

$$\text{DATAMODE}_{\text{out}} \neq \text{CC33_GRADED} \text{ and} \tag{4}$$

$$\text{DATAMODE}_{\text{out}} \neq \text{FAINT} \text{ and} \tag{5}$$

$$\text{DATAMODE}_{\text{out}} \neq \text{FAINT_BIAS} \text{ and} \tag{6}$$

$$\text{DATAMODE}_{\text{out}} \neq \text{GRADED} \text{ and} \tag{7}$$

$$\text{DATAMODE}_{\text{out}} \neq \text{VFAINT}, \tag{8}$$

then `acis_build_chip_gti` exits with an error message.

vi. If

$$\text{DATAMODE}_{\text{out}} = \text{CC33_FAINT} \text{ or} \tag{9}$$

$$\text{DATAMODE}_{\text{out}} = \text{CC33_GRADED}, \tag{10}$$

and if HDU h_{out} does not include the keywords `RA_TARG` and `DEC_TARG`, then `acis_build_chip_gti` exits with an error message. Hereafter the values of these keywords are referred to as `RA_TARGout`, and `DEC_TARGout`, respectively.

vii. If

$$\text{DATAMODE}_{\text{out}} = \text{CC33_FAINT} \text{ or} \tag{11}$$

$$\text{DATAMODE}_{\text{out}} = \text{CC33_GRADED}, \tag{12}$$

if HDU h_{out} includes the keyword `HUCLAS3`, and if `HUCLAS3 = CC_CORRECTED`, then $t_{\text{adj}} = \text{yes}$. Otherwise, $t_{\text{adj}} = \text{no}$.

viii. If HDU h_{out} does not include a binary table with the columns

- `CCD_ID` and
- `EXPNO`,

then `acis_build_chip_gti` exits with an error message. Hereafter these columns are referred to as `CCD_IDout` and `EXPNOout`, respectively.

(c) `pbkfile`:

- i. If the `pbkfile` does not exist, then `acis_build_chip_gti` exits with an error message.
- ii. If the `pbkfile` exists, but the file permissions do not allow it to be read, then `acis_build_chip_gti` exits with an error message.
- iii. If the `pbkfile` does not have an HDU h_{pbk} with the keyword

$$\text{CONTENT} = \text{PBK}, \tag{13}$$

then `acis_build_chip_gti` exits with an error message.

(d) `aspfile`:

- i. If the `aspfile` does not exist, then `acis_build_chip_gti` exits with an error message.
- ii. If the `aspfile` exists, but the file permissions do not allow it to be read, then `acis_build_chip_gti` exits with an error message.

iii. If the `aspfile` does not have an HDU h_{asp} that has the keyword

$$\text{CONTENT} = \text{ASPSOL}, \tag{14}$$

then `acis_build_chip_gti` exits with an error message.

iv. If HDU h_{asp} does not include a binary table with the columns

- DEC,
- DTHETA,
- DY,
- DZ,
- RA,
- ROLL, and
- TIME,

then `acis_build_chip_gti` exits with an error message.

(e) `nominalchip`:

i. The parameter string `nominalchip` is converted to contain only lower case letters.

ii. If

$$\text{nominalchip} \neq \text{default and} \tag{15}$$

$$\text{nominalchip} \neq 0 \text{ and} \tag{16}$$

$$\text{nominalchip} \neq 1 \text{ and} \tag{17}$$

$$\text{nominalchip} \neq 2 \text{ and} \tag{18}$$

$$\text{nominalchip} \neq 3 \text{ and} \tag{19}$$

$$\text{nominalchip} \neq 4 \text{ and} \tag{20}$$

$$\text{nominalchip} \neq 5 \text{ and} \tag{21}$$

$$\text{nominalchip} \neq 6 \text{ and} \tag{22}$$

$$\text{nominalchip} \neq 7 \text{ and} \tag{23}$$

$$\text{nominalchip} \neq 8 \text{ and} \tag{24}$$

$$\text{nominalchip} \neq 9, \tag{25}$$

then `acis_build_chip_gti` exits with an error message.

iii. If

$$\text{nominalchip} = 0 \text{ or} \tag{26}$$

$$\text{nominalchip} = 1 \text{ or} \tag{27}$$

$$\text{nominalchip} = 2 \text{ or} \tag{28}$$

$$\text{nominalchip} = 3 \text{ or} \tag{29}$$

$$\text{nominalchip} = 4 \text{ or} \tag{30}$$

$$\text{nominalchip} = 5 \text{ or} \tag{31}$$

$$\text{nominalchip} = 6 \text{ or} \tag{32}$$

$$\text{nominalchip} = 7 \text{ or} \tag{33}$$

$$\text{nominalchip} = 8 \text{ or} \tag{34}$$

$$\text{nominalchip} = 9, \tag{35}$$

then c_{aim} is the integer equivalent of the string `nominalchip`.

iv. If `nominalchip` = default, then the value of c_{aim} is determined from the input data.

2. DTCOR:

The value of DTCOR, which does not depend on the CCD_ID, is given by the following expressions.

(a) If

$$\text{DATAMODE}_{\text{out}} = \text{FAINT} \text{ or} \quad (36)$$

$$\text{DATAMODE}_{\text{out}} = \text{FAINT_BIAS} \text{ or} \quad (37)$$

$$\text{DATAMODE}_{\text{out}} = \text{GRADED} \text{ or} \quad (38)$$

$$\text{DATAMODE}_{\text{out}} = \text{VFAINT}, \quad (39)$$

then

$$\text{DTCOR} = \frac{\text{TIMEDEL}_{\text{in}} - 0.04104}{\text{TIMEDEL}_{\text{in}} + \text{FLSHTIME}_{\text{in}}}. \quad (40)$$

DTCOR includes $\text{FLSHTIME}_{\text{in}}$ because it is included in the GTIs.

(b) If

$$\text{DATAMODE}_{\text{out}} = \text{CC33_FAINT} \text{ or} \quad (41)$$

$$\text{DATAMODE}_{\text{out}} = \text{CC33_GRADED}, \quad (42)$$

then

$$\text{DTCOR} = 0.99609375 \quad (43)$$

(i.e. 510/512).

3. $\text{EXPNO}_{\text{min}}$:

The value of $\text{EXPNO}_{\text{min}}$ is determined as follows.

(a) If

$$\text{DATAMODE}_{\text{out}} = \text{FAINT} \text{ or} \quad (44)$$

$$\text{DATAMODE}_{\text{out}} = \text{FAINT_BIAS} \text{ or} \quad (45)$$

$$\text{DATAMODE}_{\text{out}} = \text{GRADED} \text{ or} \quad (46)$$

$$\text{DATAMODE}_{\text{out}} = \text{VFAINT}, \quad (47)$$

then $\text{EXPNO}_{\text{min}} = 3$.

(b) If

$$\text{DATAMODE}_{\text{out}} = \text{CC33_FAINT} \text{ or} \quad (48)$$

$$\text{DATAMODE}_{\text{out}} = \text{CC33_GRADED}, \quad (49)$$

then $\text{EXPNO}_{\text{min}} = 4$.

4. Valid CCD_IDs:

The set of valid CCD_IDs is identified. Here, CCD_ID c is defined as valid if there are one or more rows (i.e. frames) in HDU h_{in} of the `infile` where $\text{CCD_ID}_{\text{in}} = c$. If there are no valid CCD_IDs, then `acis_build_chip_gti` exits with an error message. If c_{aim} is not a valid CCD_ID, then `acis_build_chip_gti` exits with an error message.

5. For each valid CCD_ID:

The following steps are performed for each valid CCD_ID c .

(a) Identify the valid EXPNOs:

If

$$\text{CCD_ID}_{\text{in}}[r_{\text{in}}] = c, \quad (50)$$

$$\text{EXPNO}_{\text{in}}[r_{\text{in}}] \geq \text{EXPNO}_{\text{min}}, \quad (51)$$

$$\text{EVTSENT}_{\text{in}}[r_{\text{in}}] > 0, \text{ and} \quad (52)$$

$$\text{EVTSENT}_{\text{in}}[r_{\text{in}}] = N_{\text{out}}, \quad (53)$$

then $\text{EXPNO}_{\text{in}}[r_{\text{in}}]$ is valid. Here N_{out} , which is greater than or equal to zero, is the number of rows (i.e. events) where

$$\text{CCD_ID}_{\text{out}}[r_{\text{out}}] = c \text{ and} \quad (54)$$

$$\text{EXPNO}_{\text{out}}[r_{\text{out}}] = \text{EXPNO}_{\text{in}}[r_{\text{in}}] \quad (55)$$

and r_{in} and r_{out} are rows in HDUs h_{in} and h_{out} of the `infile` and `outfile`, respectively. If there are no valid EXPNOs for CCD_ID c , then `acis_build_chip_gti` exits with an error message.

(b) GTI START and STOP times:

Each consecutive set of one or more valid EXPNOs from EXPNO_i to EXPNO_j for CCD_ID c is a GTI for the CCD. The GTI START and STOP times associated with this set of EXPNOs is given by the following expressions.

i. If

$$\text{DATAMODE}_{\text{out}} = \text{FAINT} \text{ or} \quad (56)$$

$$\text{DATAMODE}_{\text{out}} = \text{FAINT_BIAS} \text{ or} \quad (57)$$

$$\text{DATAMODE}_{\text{out}} = \text{GRADED} \text{ or} \quad (58)$$

$$\text{DATAMODE}_{\text{out}} = \text{VFAINT}, \quad (59)$$

then

$$\text{START} = \text{TIME}_{\text{in}}[r_{\text{in},i}] - \text{TIMEPIXR}_{\text{in}} \times \text{TIMEDEL}_{\text{in}} - \text{FLSHTIME}_{\text{in}} \text{ and} \quad (60)$$

$$\text{STOP} = \text{TIME}_{\text{in}}[r_{\text{in},j}] + (1 - \text{TIMEPIXR}_{\text{in}}) \times \text{TIMEDEL}_{\text{in}}, \quad (61)$$

where the row $r_{\text{in},i}$ is the one where

$$\text{CCD_ID}_{\text{in}}[r_{\text{in},i}] = c \text{ and} \quad (62)$$

$$\text{EXPNO}_{\text{in}}[r_{\text{in},i}] = \text{EXPNO}_i \quad (63)$$

and the row $r_{\text{in},j}$ is the one where

$$\text{CCD_ID}_{\text{in}}[r_{\text{in},j}] = c \text{ and} \quad (64)$$

$$\text{EXPNO}_{\text{in}}[r_{\text{in},j}] = \text{EXPNO}_j. \quad (65)$$

The GTIs include the $\text{FLSHTIME}_{\text{in}}$ because `DTCOR` includes it.

ii. If

$$\text{DATAMODE}_{\text{out}} = \text{CC33_FAINT} \text{ or} \quad (66)$$

$$\text{DATAMODE}_{\text{out}} = \text{CC33_GRADED} \quad (67)$$

and if $t_{\text{adj}} = \text{yes}$, then

$$\text{START} = \text{TIME}_{\text{in}}[r_{\text{in},i}] - \text{TIMEPIXR}_{\text{in}} \times \text{TIMEDEL}_{\text{in}} \text{ and} \quad (68)$$

$$\text{STOP} = \text{TIME}_{\text{in}}[r_{\text{in},j}] + (1 - \text{TIMEPIXR}_{\text{in}}) \times \text{TIMEDEL}_{\text{in}}. \quad (69)$$

iii. If

$$\text{DATAMODE}_{\text{out}} = \text{CC33_FAINT} \text{ or} \quad (70)$$

$$\text{DATAMODE}_{\text{out}} = \text{CC33_GRADED} \quad (71)$$

and if $t_{\text{adj}} = \text{no}$, then

$$\begin{aligned} \text{START} &= \text{TIME}_{\text{in}}[r_{\text{in},i}] - \text{TIMEPIXR}_{\text{in}} \times \text{TIMEDEL}_{\text{in}} + \\ &(\text{CHIPY_TARG}[\text{TIME}_{\text{in}}[r_{\text{in},i}] + 1028] \times 0.00285 \text{ and} \end{aligned} \quad (72)$$

$$\begin{aligned} \text{STOP} &= \text{TIME}_{\text{in}}[r_{\text{in},j}] + (1 - \text{TIMEPIXR}_{\text{in}}) \times \text{TIMEDEL}_{\text{in}} + \\ &(\text{CHIPY_TARG}[\text{TIME}_{\text{in}}[r_{\text{in},j}] + 1028] \times 0.00285, \end{aligned} \quad (73)$$

where $\text{CHIPY_TARG}[\text{TIME}_{\text{in}}[r_{\text{in},i}]]$ and $\text{CHIPY_TARG}[\text{TIME}_{\text{in}}[r_{\text{in},j}]]$ are the CHIPY locations of the sky coordinates $\text{RA_TARG}_{\text{out}}$ and $\text{DEC_TARG}_{\text{out}}$ at the times $\text{TIME}_{\text{in}}[r_{\text{in},i}]$ and $\text{TIME}_{\text{in}}[r_{\text{in},j}]$, respectively. The `aspfile`, `geompar`, and `pixlib` are used to determine the values of $\text{CHIPY_TARG}[\text{TIME}_{\text{in}}[r_{\text{in},i}]]$ and $\text{CHIPY_TARG}[\text{TIME}_{\text{in}}[r_{\text{in},j}]]$.

(c) **ONTIME c** :

The value of **ONTIME c** is given by

$$\text{ONTIME}_c = \sum_k (\text{STOP}_k - \text{START}_k), \quad (74)$$

where START_k and STOP_k are the **START** and **STOP** times, respectively, of the k^{th} GTI for **CCD_ID** c .

(d) **LIVTIME c** :

The value of **LIVTIME c** is given by

$$\text{LIVTIME}_c = \text{ONTIME}_c \times \text{DTCOR}. \quad (75)$$

(e) **EXPOSUR c** :

The value of **EXPOSUR c** is given by

$$\text{EXPOSUR}_c = \text{ONTIME}_c \times \text{DTCOR} \quad (76)$$

(i.e. $\text{EXPOSUR}_c = \text{LIVTIME}_c$).

6. Aim-point CCD:

If the **CCD_ID** $c = c_{\text{aim}}$, then

$$\text{ONTIME} = \text{ONTIME}_c, \quad (77)$$

$$\text{LIVETIME} = \text{LIVTIME}_c, \text{ and} \quad (78)$$

$$\text{EXPOSURE} = \text{EXPOSUR}_c. \quad (79)$$

7. Write output:

(a) The HDU h_{out} of the `outfile` is modified to include the keywords

- **DTCOR**,
- **EXPOSURE**,
- **EXPOSUR c** (one such keyword for each valid **CCD_ID**),
- **LIVETIME**,
- **LIVTIME c** (one such keyword for each valid **CCD_ID**),
- **ONTIME**, and

- `ONTIMEc` (one such keyword for each valid `CCD_ID`),
- (b) The `outfile` is modified to include a GTI HDU for each valid CCD. Each one of these HDUs includes a binary table with the columns
- `START` and
 - `STOP`.

These columns include one row for each GTI for the CCD.

1.6 TBD

- Are there `DATAMODEs` other than `CC33_FAINT`, `CC33_GRADED`, `FAINT`, `FAINT_BIAS`, `GRADED`, and `VFAINT` that should be included?
- How is the aim-point `CCD_ID` determined? `DETNAM`? `SIM_Z`? $(X, Y) = (4096.5, 4096.5)$?
- Is there a systematic offset for the mission-timeline GTIs with respect to the GTIs produced by `acis_build_chip_gti`?
- How can the mission-timeline GTIs be merged with the `acis_build_chip_gti` GTIs so that they are aligned with the frame boundaries?